digital™

Getting Started with the Online Documentation Library (ODL) CD–ROM

AV–R5G1K–TE

Dear Online Documentation Library Customer,

This Compaq Tru64™ UNIX® ODL uses the Bookshelf Navigation Utility (BNU) as the primary interface to online bookshelves. Bookshelves contain books in a variety of formats including Bookreader™, HTML, and Adobe® Acrobat®. The BNU invokes the appropriate viewer to display each book.

In mounting the ODL CD–ROM, the device name for the CD–ROM reader will vary according to your system configuration and the version of Compaq Tru64 UNIX installed.

In addition to scalability, clustering, system management, file system, networking, installation, and other enhancements and new features with Tru64 UNIX V5.0 comes full support for FibreChannel, SCSI-3, and wide SCSI devices. The implementation of this support required a major change to the Tru64 UNIX device naming scheme, which is reflected in the following description.

The example commands make the following assumptions:

- You are logged in as superuser (root).
- If the version of Tru64 UNIX installed is V5.0 or higher, then the CD–ROM reader device is /dev/disk/cdrom0c. This value can be obtained for your system using the following command.

  ```
  # /sbin/hwmgr -view devices
  ```

  Otherwise, the CD–ROM reader device is /dev/rz4c. The device unit for the CD–ROM, 4 in this case, can be obtained for your system by using the following command.

  ```
  # file /dev/rrz*c
  ```

  Look for the line in the output that contains the prefix *RRD*.
- The CD–ROM label is U99Q4_1.

The steps involved in installing the ODL, including example commands, are summarized below.

1. Create the mount point directory.

   ```
   # mkdir -p /usr/share/doclib/ODL/U99Q4_1
   ```

2. Insert the ODL CD–ROM into the CD–ROM reader.
3. Mount the ODL CD–ROM on the mount point directory. For Tru64 UNIX V5.0 and higher:

   ```
   # mount -r /dev/disk/cdrom0c /usr/share/doclib/ODL/U99Q4_1
   ```

   For versions of Tru64 UNIX lower than V5.0:

   ```
   # mount -r /dev/rz4c /usr/share/doclib/ODL/U99Q4_1
   ```

4. Change directory to the setup directory.

```
# cd /usr/share/doclib/ODL/U99Q4_1/setup
```

5. Run the setup script.

```
# ./setup.scp
```

6. Exit the Common Desktop Environment (CDE) session and log back in using a non-root user name.

7. Run BNU.

```
% bnu
```

For BNU system requirements and more detailed installation instructions, refer to the *Online Documentation Library CD–ROM User's Guide*, which is available online or in the readme/ directory in the following formats: *readme* directory on disc 1:

```
readme/odl_ug.ps, .txt, .bkb
```

Your Feedback Is Appreciated

We look forward to your comment and feedback and encourage you to provide any information on the new features being initiated within the Online Documentation Library. You can send comments via electronic mail to:

```
cdrom_docs@zko.dec.com
```

© Digital Equipment Corporation. 1999. All rights reserved.

® Compaq, the Compaq logo, and the DIGITAL logo are registered in the United States Patent and Trademark Office.

™ Bookreader, DIGITAL, and Tru64 are trademarks of Compaq Computer Corporation.

® Adobe and Acrobat are registered trademarks of Adobe Systems Incorporated. UNIX is a registered trademark in the United States and other countries, licensed exclusively through X/Open Company, Ltd.